TÜV Rheinland (China) Ltd. Member of TÜV Rheinland Group



TPV Electronics (Fujian) Co., Ltd. Mr. Xinliang Wu RD-SE Rongqiao Economic and Technological Development Zone Fuqing City, Fujian Province P.R. China

Date : 18.01.2016 Our ref. : WangAn ZJ Your ref.: 1140023533

Ref : CB Certificate Japan

Type of Equipment : LCD MONITOR Model Designation : See Certificate Certificate No. : JPTUV-067398-M1 Report No. : 17051179 002

Dear Mr. Xinliang Wu,

Thank you very much for your interest in our services.

Please find enclosed your certification documents.

We appreciate your support and would like to offer our assistance in the approval of your future products through our extensive range of technical services.

Please feel free to contact us whatever your requirements may be.

With kind regards,

Certification Body

Ing. M. Eichenseder

Enclosure

证书的详细资料请登陆www.certipedia.com查阅,或拨打我司客服热线800 999 3668 / 400 883 1300咨询

TÜV Rheinland (China) Ltd. 莱茵检测认证服务(中国)有限公司 Unit 707, AVIC Bldg., No. 10B, Central Road, East 3rd Ring Road, Chaoyang District, Beijing, 100022, P.R.China

北京市朝阳区东三环中路乙10号 艾维克大厦707室 邮编: 100022 Tel: (8610)6566 6660 Fax: (8610)6566 6667 e-mail: info@bj.chn.tuv.com Internet: http://www.chn.tuv.com



Ref. Certif. No.

JPTUV-067398-M1

IEC SYSTEM FOR MUTUAL RECOGNITION OF TEST CERTIFICATES FOR ELECTRICAL EQUIPMENT (IECEE) CB SCHEME

SYSTEME CEI D'ACCEPTATION MUTUELLE DE CERTIFICATS D ESSAIS DES EQUIPEMENTS ELECTRIQUES (IECEE) METHODE OC

CB TEST CERTIFICATE

CERTIFICAT D'ESSAI OC

Product Produit	LCD MONITOR
Name and address of the applicant Nom et adresse du demandeur	TPV Electronics (Fujian) Co., Ltd. Rongqiao Economic and Technological Development Zone, Fuqing City, Fujian Province, P.R. China
Name and address of the manufacturer Nom et adresse du fabricant	TPV Electronics (Fujian) Co., Ltd. Rongqiao Economic and Technological Development Zone, Fuqing City, Fujian Province, P.R. China
Name and address of the factory Nom et adresse de l'usine	See additional page(s)
Ratings and principal characteristics Valeurs nominales et charactéristiques principales	AC 100-240V; 50/60Hz; 1.5A; Class I
Trademark (if any) Marque de fabrique (si elle existe)	AOC
Type of Manufacturer's Testing Laboratories used Type de programme du laboratoire d'essais constructeur	N/A
Model / Type Ref. Ref. de type	270LM000**, *2775*******, *277*******; 236LM000**, *2475*******, *247******** (* = 0-9, A-Z, a-z, -, /, + or blank)
Additional information (if necessary may also be reported on page 2) Les informations complémentaires (si nécessaire, peuvent être indiqués sur la 2 ^{ème} page)	For model difference, refer to the test report. Re-issue of JPTUV-067398 dated 12.11.2015, due to first modification.
A sample of the product was tested and found to be in conformity with Un échantillon de ce produit a été essayé et a été considéré conforme à la	IEC 60950-1:2005 + A1 + A2 National differences see test report
As shown in the Test Report Ref. No. which forms part of this Certificate Comme indiqué dans le Rapport d'essais numéro de référence qui constitue partie de ce Certificat	17051179 002
This CB Test Certificate is issued by the National Certification Ce Certificat d'essai OC est établi par l'Organisme National d	



TÜV Rheinland Japan Ltd. Global Technology Assessment Center 4-25-2 Kita-Yamata, Tsuzuki-ku Yokohama 224-0021 Japan Phone + 81 45 914-3888 Fax + 81 45 914-3354 Mail: info@jpn.tuv.com Web: www.tuv.com

Signature:



Date:

0/061 CB 05.12

Ref. Certif. No.



JPTUV-067398-M1

PAGE 2 OF 3

- TPV Display Technology (Wuhan) Co., Ltd. Unique No. 11, Zhuankou Development District of Economic Technological Development Zone, Wuhan City 430056, P.R. China
- TPV Electronics (Fujian) Co., Ltd. Shangzheng, Yuan Hong Road Fuqing City, Fujian Province P.R. China
- Envision Industry of Electronic Products Ltd. Rodovia Anhanguera S/N-KM 49 Tijuco Preto-Jundiaí-SP-13.205-700, Brazil
- L&T Display Technology (Fujian) Ltd. Optoelectronic Park, Rongqiao Economic and Technological Development Zone Fuqing, Fujian 350301, P.R. China
- 5. TPV Electronics (Fujian) Co., Ltd. Rongqiao Economic and Technological Development Zone Fuqing City, Fujian Province P.R. China
- Trend Smart CE Mexico S de RL de CV Avenida Sor Juana Ines de la Cruz de 19602 Nueva Tijuana, 22435 Tijuana Baja California MEXICO
- TPV Display Technology (Beihai) Co., Ltd.
 China Electronic Beihai Industry Park, Northeast of the Crossing Between Taiwan Road and Jilin Road, Beihai City, Guangxi, P.R. China
- TPV Technology (Qingdao) Co., Ltd.
 No.99 Huoju Road, High-tech Industrial Development Zone Qingdao City, Shandong Province, P.R. China
- TPV Display Technology (China) Co., Ltd.
 No. 106 Jinghai 3 Rd., BDA Beijing City 100176 P.R. China

Additional information (if necessary) Information complémentaire (si nécessaire)

Report Ref. No.: 17051179 002

Signature:

Ing. M. Eichenseder

Ref. Certif. No.



JPTUV-067398-M1

PAGE 3 OF 3

- Hefei Huntkey Display Technology Co., Ltd.
 South Jinxiu Road, East Qingtan Road Economic And Technological Development Zone, Hefei, Anhui 230601, P.R. China
- TPV Electronics (Fujian) Co., Ltd. Optoelectronic Park, Rongqiao Economic and Technological Development Zone, Fuqing City, Fujian Province 350301, P.R. China

Additional information (if necessary) Information complémentaire (si **nécessaire**)

Report Ref. No.: 17051179 002

Ing. M. Eichenseder

Signature:



Test Report issued under the responsibility of:



TEST REPORT IEC 60950-1 Information technology equipment – Safety – Part 1: General requirements

Report Number:	17051179 002
Date of issue:	Jan. 14. 2016
Total number of pages	45
Applicant's name:	TPV Electronics (Fujian) Co., Ltd.
Address:	Rongqiao Economic and Technological Development Zone, Fuqing City, Fujian Province, P.R.China
Test specification:	
Standard:	IEC 60950-1:2005 (Second Edition) + Am 1:2009 + Am 2:2013
Test procedure:	CB Scheme
Non-standard test method:	N/A
Test Report Form No:	IEC60950_1F
Test Report Form(s) Originator:	SGS Fimko Ltd
Master TRF:	Dated 2014-02
Copyright © 2014 IEC System of Co and Components (IECEE System). A	nformity Assessment Schemes for Electrotechnical Equipment III rights reserved.
	in part for non-commercial purposes as long as the IECEE is acknowledged as EE takes no responsibility for and will not assume liability for damages resulting ad material due to its placement and context.
If this Test Report Form is used by nor CB Scheme procedure shall be remov	n-IECEE members, the IECEE/IEC logo and the reference to the ed.
	Report unless signed by an approved CB Testing Laboratory te issued by an NCB in accordance with IECEE 02.
General disclaimer:	
	relate only to the object tested. Sept in full, without the written approval of the Issuing CB Testing Report and its contents can be verified by contacting the NCB,
Test item description:	CD MONITOR
Trade Mark	
Manufacturer	
	270LM000**, *2775*******, * 277 *******; 236LM000** , * 2475 ********,
	247 ************ (* can be A-Z, a-z, 0-9, +, -, /, \ or blank, for marketing use only; No constructional differences. Models differ only in model name and marking label)

Ratings: I/P: 100-240Vac, 50/60Hz, 1.5A

Testing procedure and testing location:	
CB Testing Laboratory:	TÜV Rheinland (Shenzhen) Co., Ltd.
Testing location/ address:	East of F/1, F/2~F/4, Building 1, Cybio Technology Building No. 6 Langshan No.2 Road, North Hi-tech Industry Park 518057 Shenzhen Nanshan District CHINA
Associated CB Testing Laboratory:	
Testing location/ address:	11
Tested by (name + signature):	Anderson Wang
Approved by (name + signature):	Steven Lin Stal.
Testing location/ address: Tested by (name + signature)	
Approved by (name + signature):	
Approved by (name + signature)	
Testing procedure: WMT/CTF Stage 2:	
Testing location/ address:	
Tested by (name + signature):	
Witnessed by (name + signature):	
Approved by (name + signature):	
Testing procedure: SMT/CTF Stage 3 or 4:	
Testing location/ address:	
Tested by (name + signature):	
Witnessed by (name + signature):	
Approved by (name + signature):	
Supervised by (name + signature):	

List of Attachments (including a total number of pages in each attachment):

- Photo documentation

Total number of pages in each attachment is indicated in individual attachment.

Input Current Test1.6.2Energy hazard in Operator Access Area2.1.1Discharge of Capacitors2.1.1SELV limits for Normal Conditions2.2.2SELV limits for Abnormal Conditions2.2.3Limited current circuits2.4Limited power source2.5Resistance of Earthing Circuit2.6.3Humidity Conditioning2.9.2Working Voltage over Insulation2.10.3Clearance and creepage distance measurements2.10.3Stability test4.1Steady force test, 10 N4.2.2	clause number 2. .5 .7 2. 3. 3.4 2. 2. 3 & 2.10.4	All tests as described in Test Case an Measurement Sections were performed at the laboratory described on page 2
Input Current Test1.6.2Input Current Test1.6.2Energy hazard in Operator Access Area2.1.1Discharge of Capacitors2.1.1SELV limits for Normal Conditions2.2.2SELV limits for Abnormal Conditions2.2.3Limited current circuits2.4Limited power source2.5Resistance of Earthing Circuit2.6.3Humidity Conditioning2.9.2Working Voltage over Insulation2.10.3Clearance and creepage distance measurements2.10.3Stability test4.1Steady force test, 10 N4.2.2	2 .5 .7 2 3 .4 2 .3 & 2.10.4	performed at the laboratory described
Energy hazard in Operator Access Area2.1.1Discharge of Capacitors2.1.1SELV limits for Normal Conditions2.2.2SELV limits for Abnormal Conditions2.2.3Limited current circuits2.4Limited power source2.5Resistance of Earthing Circuit2.6.3Humidity Conditioning2.9.2Working Voltage over Insulation2.10.3Clearance and creepage distance measurements2.10.3Stability test4.1Steady force test, 10 N4.2.2	.5 .7 2 3 3.4 2 2 3 & 2.10.4	
Discharge of Capacitors2.1.1Discharge of Capacitors2.1.1SELV limits for Normal Conditions2.2.2SELV limits for Abnormal Conditions2.2.3Limited current circuits2.4Limited power source2.5Resistance of Earthing Circuit2.6.3Humidity Conditioning2.9.2Working Voltage over Insulation2.10.3Clearance and creepage distance measurements2.10.3Stability test4.1Steady force test, 10 N4.2.2	.7 2 3 4.4 2 2 3 & 2.10.4	
SELV limits for Normal Conditions2.2.2SELV limits for Abnormal Conditions2.2.3Limited current circuits2.4Limited power source2.5Resistance of Earthing Circuit2.6.3Humidity Conditioning2.9.2Working Voltage over Insulation2.10.3Clearance and creepage distance measurements2.10.3Stability test4.1Steady force test, 10 N4.2.2	2 3 3.4 2 2 3 & 2.10.4	
SELV limits for Abnormal Conditions2.2.3Limited current circuits2.4Limited power source2.5Resistance of Earthing Circuit2.6.3Humidity Conditioning2.9.2Working Voltage over Insulation2.10.3Clearance and creepage distance measurements2.10.3Stability test4.1Steady force test, 10 N4.2.2	3 3.4 2 2 3 & 2.10.4	
Limited current circuits2.4Limited power source2.5Resistance of Earthing Circuit2.6.3Humidity Conditioning2.9.2Working Voltage over Insulation2.10.1Clearance and creepage distance measurements2.10.1Stability test4.1Steady force test, 10 N4.2.2	3.4 2 2 3 & 2.10.4	
Limited power source2.5Resistance of Earthing Circuit2.6.3Humidity Conditioning2.9.2Working Voltage over Insulation2.10.3Clearance and creepage distance measurements2.10.3Stability test4.1Steady force test, 10 N4.2.2	2 3 & 2.10.4	
Resistance of Earthing Circuit2.6.3Humidity Conditioning2.9.2Working Voltage over Insulation2.10.1Clearance and creepage distance measurements2.10.1Stability test4.1Steady force test, 10 N4.2.2	2 3 & 2.10.4	
Humidity Conditioning2.9.2Working Voltage over Insulation2.10.3Clearance and creepage distance measurements2.10.3Stability test4.1Steady force test, 10 N4.2.2	2 3 & 2.10.4	
Working Voltage over Insulation 2.10.1 Clearance and creepage distance measurements 2.10.1 Stability test 4.1 Steady force test, 10 N 4.2.2	2 3 & 2.10.4	
Clearance and creepage distance measurements2.10.3Stability test4.1Steady force test, 10 N4.2.2	3 & 2.10.4	
measurements 2.10. Stability test 4.1 Steady force test, 10 N 4.2.2		
Steady force test, 10 N 4.2.2		
Steady Force Test 30N 4.2.3		
4.2.0	1	
Steady Force Test, 250N 4.2.4		
Impact Test (Steel Ball) 4.2.5		
Stress Relief Test 4.2.7	l.	
Wall or ceiling mounted 4.2.10	0	
Maximum Temperature Test 4.5.2	l	
Ball pressure test 4.5.5		
Openings in enclosures 4.6		
Touch Current and PE current 5.1.6	i.	
Electric Strength Test 5.2		
Fault Condition Test 5.3		
he EUT passed the test.		

Copy of marking plate	
The artwork below may be only a draft. The use of certificative respective NCBs that own these marks.	tion marks on a product must be authorized by
ACC LCD MONITOR/液晶顯示器/모니터 Product Name/Nama Produk/機種名/제품명: E2475SWJ 236LM00031 Power Rating/Tegangan/額定電源/정격입력:100-240V ~ 50/60Hz 1.5A 제조국:중국/中國製造/ Made In China / Buatan China www.aoc.com Q40G024N-615-75A	CAN ICES-3(B)/NMB-3(B) Laite on liitettava suojakoskettimilla varustettuun pistorasiaan Apparatet må tilkoples jordet stikkontakt Apparaten skall anslutas till jordat uttag Apparatets stikprop skal tilsluttes en stikkontakt med jord, som giver forbindelse til stikproppens jord BARCODE
Warning: Shock Hazard, Do Not Open. 高壓注意:非專業維修人員請勿打開後蓋。 警語:使用過度恐傷害視力 Rongqiao Economic and Technological Development Zone, Fuqing City, Fujian Province, P.R.China 福建捷聯電子有限公司 福建信福清市融僑經演技術開發區 판매원·(주)알파스캔디스플레이 수입원 : COMPOINT CO., LTD. 상호명 : TPV Electronics(Fujian) Co., Ltd. 제조A/S 문의치:1544-7739 Q40G024N-615-76A	stelgebouw, Bernhardplein Insterdam
ADC LCD MONITOR/液晶显示器/液晶顯示器/모니터 Product Name/Nama Produk/机种名/機種名/모델명: Q2775PQU Model No. 型号/型號/모델명: Q270LM00023 Power Rating/Tegangan/額定电源/額定電源/정객입력: 100-240V ~ 50/60Hz 1.5A Q40G027N-615-49A	CAN ICES-3(B)/NMB-3(B) Laite on liitettävä suojakoskettimilla varustettuun pistorasiaan Apparatet må tilkopies jordet stikkontakt Apparaten skall anslutas till jordat uttag Apparatets stikprop skal tilsluttes en stikkontakt med jord, som giver forbindelse til stikproppens jord
Warning: Shock Hazard, Do Not Open. 高座注意:非专业维修人员请勿打开后盖。 高壓注意:非專業維修人員請勿打開後蓋。 警語:使用過度恐傷害視力 不至[체명 / 拉호명 : TPV Electronics(Fujian) Co., Ltd Rongqiao Economic and Technological Development Zone, Fuqing City, Fujian Province, P.R. China 판매원 : 예양말파스캔디스플레이 제조A/S 문의치 : 1544 7739 福建捷联电子有限公司 福建省福清市融僑經濟技術開發區 Q40G027N-615-50A	elgebouw, WWW.aoc.com nhardplein Made in China / Buatan China

Page 5 of 45

Test item particulars:	
Equipment mobility:	[x] movable (for unit with base stand) [] hand-held [] transportable [x] stationary (for unit without base stand) [] for building-in [] direct plug-in
Connection to the mains:	 [x] pluggable equipment [x] type A [] type B [] permanent connection [x] detachable power supply cord [] non-detachable power supply cord [] not directly connected to the mains
Operating condition:	[x] continuous [] rated operating / resting time:
Access location:	[x] operator accessible [] restricted access location
Over voltage category (OVC):	[] OVC I [x] OVC II [] OVC III [] OVC IV [] other:
Mains supply tolerance (%) or absolute mains supply values:	±10% according to client's request
Tested for IT power systems:	[] Yes [x] No
IT testing, phase-phase voltage (V):	
Class of equipment:	[x] Class I [] Class II [] Class III [] Not classified
Considered current rating of protective device as part of the building installation (A)	16A (20A for North America)
Pollution degree (PD)	[] PD 1 [x] PD 2 [] PD 3
IP protection class:	IP20
Altitude during operation (m):	≤5000
Altitude of test laboratory (m):	
Mass of equipment (kg):	For 27 models without base: 4.21kg; For 23.6 models without base: 3.15kg; base type A: 3.59kg; base type B: 0.46kg; base type A': 2.01kg; base type B': 0.36kg
Possible test case verdicts:	
- test case does not apply to the test object::	N/A
- test object does meet the requirement:	P (Pass)
- test object does not meet the requirement::	F (Fail)
Testing:	
Date of receipt of test item:	Dec.01.2015
Date(s) of performance of tests:	Dec.24.2015 - Jan.11.2016
General remarks:	
"(see Enclosure #)" refers to additional information ap "(see appended table)" refers to a table appended to the	
Throughout this report a 🗌 comma / 🔀 point is u	sed as the decimal separator.

		F	Page 6 of 45			Report No. 17	051179 002
Manufacturer's Decl	aration per	sub-clause	e 4.2.5 of IE	CEE 02:			
The application for ob- Certificate includes ma location and a declara stating that the sample evaluation is (are) rep from each factory has	ore than one ation from the e(s) submitte resentative o	e factory e Manufactu ed for of the produ	icts	s t applicable			
When differences ex							
Name and address of		es)	: See or	iginal report	17051179 001	for factory lis	t.
General product info							
Description of change	e(s):						
1. Add new powe	er board: 715	G7775 for	27 inch mod	lels.			
2. Add new main board 715G77		G5436 and	d 715G7612	for 27 inch r	nodels, which	are used with	power
3. Change rating See Page 4 for			el from "50-	60Hz" to " 50	/60Hz" accord	ing to client's r	request.
4. Change model	name "*277	/***" to "* 27	7******************	No technical	difference exis	sts.	
5. Add new statio adjustable base						hile, original H	eight
6. Update weight the details.	of 27 inch m	nodels due	to typing err	or in original	report 170511	79 001. See F	Page 5 for
 7. Add new 23.6 i model 270LM0 used with new used with new used with plas used with bas For the above described 	000**, excep w power boa w main board stic enclosur USB board; se type A' an	t for: rd 715G77 d 715G543 re type A' a nd type B'.	75 only; 6 and 715G ind metal en	7970 only; closure type	B;	are identical to	o original
Change Testin			.9	Comments			
	Summary of e details.	f testing" o	on Page 3	See follow	ing pages for t	he details.	
See below table for di	ifferences ar	mong the m	nodels:				
	anel size	Power board	Plasitc enclosure	Metal enclosure	Main board	USB board	Base
270LM000** *2775*******		15G7760	Time A	Tume	715G7742 715G7762	715G7743	Туре А
*277*******	27 inch 7	15G7775	Туре А	Туре А	715G5436 715G7612	N/A	Туре В
236LM000** * 2475 ******** 23 * 247 *********	3.6 inch 7	15G7775	Туре А'	Туре В	715G5436 715G7970	N/A	Type A' Type B'

Supplementary information:

- Metal enclosure type B is identical to type A except for adding some circle opening near secondary circuit of power board;
- 2. Plastic enclosure type A is identical to type A' except for dimension due to difference panel size.
- 3. Base type A', B' are similar to type A, B except for smaller dimension.

Definition of variable(s):

Variable:	Range of variable:	Content:
*	A-Z, a-z, 0-9, +, -, /, \ or blank	For marketing use only; No constructional differences. Models differ only in model name and marking label

Other comments:

Declaration of the manufacturer: the sample(s) submitted for evaluation is (are) representative of the products from each factory.

<u>History of amendments and modifications:</u> Ref. No. 17051179 001 dated Nov. 10. 2015 (original test report) Ref. No. 17051179 002 dated Jan. 12. 2016 (modification)

Abbreviations used in the	e report:		
 normal conditions functional insulation double insulation between parts of opposite 	N.C. OP DI	 single fault conditions basic insulation supplementary insulation 	S.F.C BI SI
polarity	BOP	- reinforced insulation	RI
Indicate used abbreviations	s (if any)		

Report No. 17051179 002

IEC 60950-1

Clause	Requirement + Test	Result - Remark	Verdict
1	GENERAL		Р

1.5	Components		Р
1.5.1	General		Р
	Comply with IEC 60950-1 or relevant component standard	(see appended table 1.5.1)	Р
1.5.2	Evaluation and testing of components	Components which are certified to IEC and/or national standards are used correctly within their ratings. Components not covered by IEC standards are tested under the conditions present in the equipment.	Ρ
1.5.3	Thermal controls	No thermal controls.	N/A
1.5.4	Transformers	Transformers used are suitable for their intended application and comply with the relevant requirements of the standard and particularly Annex C.	Ρ
1.5.5	Interconnecting cables	Interconnecting cable does not carry voltage higher than SELV and no higher energy level than 240VA.	Ρ
1.5.6	Capacitors bridging insulation	Between lines: X1 or X2 capacitor according to IEC 60384-14 was used.	Ρ
		Between primary and earth: Y1 or Y2 capacitors according to IEC 60384-14 were used.	
		Between primary and secondary: Y1 capacitor according to IEC 60384-14 was used.	
		(see appended table 1.5.1)	
1.5.7	Resistors bridging insulation		Ρ
1.5.7.1	Resistors bridging functional, basic or supplementary insulation	Only discharge resistors bridging between L-N (functional)	Ρ
1.5.7.2	Resistors bridging double or reinforced insulation between a.c. mains and other circuits		N/A
1.5.7.3	Resistors bridging double or reinforced insulation between a.c. mains and antenna or coaxial cable		N/A
1.5.8	Components in equipment for IT power systems		N/A

Page 9 of 45

 	~~	~ -	
EC	60	95	0-1

Clause	Requirement + Test	Result - Remark	Verdict
	- F		
1.5.9	Surge suppressors		N/A
1.5.9.1	General		N/A
1.5.9.2	Protection of VDRs		N/A
1.5.9.3	Bridging of functional insulation by a VDR		N/A
1.5.9.4	Bridging of basic insulation by a VDR	No such construction.	N/A
1.5.9.5	Bridging of supplementary, double or reinforced insulation by a VDR	No such construction.	N/A

1.6	Power interface		Р
1.6.1	AC power distribution systems	TN power system	Р
1.6.2	Input current	(see appended table 1.6.2)	Р

1.7	Marking and instructions		Р
1.7.1	Power rating and identification markings	See below.	Р
1.7.1.1	Power rating marking	See below.	Р
	Multiple mains supply connections		N/A
	Rated voltage(s) or voltage range(s) (V)	See copy of marking plate for details	Р
	Symbol for nature of supply, for d.c. only	AC source	N/A
	Rated frequency or rated frequency range (Hz):	See copy of marking plate for details	Р
	Rated current (mA or A)	See copy of marking plate for details	Р
1.7.1.2	Identification markings	See below.	Р
	Manufacturer's name or trade-mark or identification mark	See copy of marking plate for details	Р
	Model identification or type reference	See copy of marking plate for details	Р
	Symbol for Class II equipment only	Class I equipment.	N/A
	Other markings and symbols	Additional symbol or marking does not give rise to misunderstanding.	Р
1.7.1.3	Use of graphical symbols	Graphical symbols used according to IEC 60417 or ISO 3864-2 or ISO 7000.	Р
1.7.2	Safety instructions and marking	English safety instruction provided.	Р
1.7.2.1	General		Р

Report No. 17051179 002

Page 10 of 45

	IEC 60950-1		
Clause	Requirement + Test	Result - Remark	Verdict
1.7.2.2	Disconnect devices	AC inlet serves as disconnect device.	Р
1.7.2.3	Overcurrent protective device	Not type B pluggable equipment or permanently connected equipment.	N/A
1.7.2.4	IT power distribution systems	TN power system.	N/A
1.7.2.5	Operator access with a tool	No such access required.	N/A
1.7.2.6	Ozone	Ozone not used or generated.	N/A
1.7.3	Short duty cycles	Equipment is designed for continuous operation.	N/A
1.7.4	Supply voltage adjustment	Single input voltage range without adjustment.	N/A
	Methods and means of adjustment; reference to installation instructions		N/A
1.7.5	Power outlets on the equipment	No power outlets provided.	N/A
1.7.6	Fuse identification (marking, special fusing characteristics, cross-reference)	The fuse marking is marked near fuse on PCB as follow: F9901(on primary): T4AL/250Vac	Ρ
		CAUTION: RISK OF FIRE REPLACE ONLY WITH SAME TYPE AND RATING OF FUSE.	
		Build-in fuses F901 (secondary T4AL/250V marked on PCB) and F801 (secondary T2AL/250V marked on PCB).	
		Not located in operator access areas.	
1.7.7	Wiring terminals	See below.	Р
1.7.7.1	Protective earthing and bonding terminals	AC inlet used. Symbol marked beside earthing pin of AC inlet	Р

2	PROTECTION FROM HAZARDS		Р
2.1	Protection from electric shock and energy hazards		Р
2.1.1	Protection in operator access areas	Only SELV signal interface accessible by operator.	Р

Page 11 of 45

Report No. 17051179 002

IEC 60950-1			
Clause	Requirement + Test	Result - Remark	Verdict
2.1.1.5	Energy hazards:	The energy does not exceed 240VA between any two points in accessible connector of secondary circuit. (see appended table 2.1.1.5.)	Ρ
2.1.1.7	Discharge of capacitors in equipment	(See appended table 2.1.1.7)	Р
	Measured voltage (V); time-constant (s)	(See appended table 2.1.1.7)	

2.2	SELV circuits		Р
2.2.1	General requirements	The secondary circuits were tested as SELV. See sub- clauses 2.2.1 to 2.2.4.	Ρ
2.2.2	Voltages under normal conditions (V)	42.4V peak or 60V d.c. are not exceeded in SELV circuit under normal operation.	Ρ
2.2.3	Voltages under fault conditions (V):	Single fault did not cause excessive voltage in accessible SELV circuits. Limits of 71V peak and 120V d.c. were not exceeded within 0.2 sec. and limits 42.4V peak and 60V d.c. were not exceeded for longer than 0.2 sec., see appended tables 2.2 and 5.3.	Ρ
2.2.4	Connection of SELV circuits to other circuits:	See sub-clauses 2.2.2 and 2.2.3. No direct connection between SELV and any primary circuits.	Ρ

2.4	Limited current circuits		Р
2.4.1	General requirements	Primary and secondary circuits bridged by Y1 type capacitor C9904. The pin connected with secondary circuits was disconnected and the measuring instrument of Figure D.1 in Annex D was connected between secondary pin and earth during the test.	Ρ
2.4.2	Limit values	(see appended table 2.4.2)	Р
	Frequency (Hz):		
	Measured current (mA):		

Page 12 of 45

Report No. 17051179 002

IEC 60950-1

Clause	Requirement + Test	Result - Remark	Verdict
	Measured voltage (V)		
	Measured voltage (V)		
2.4.3	Connection of limited current circuits to other circuits	Only intended to be connected with SELV circuits.	Р

2.5	Limited power sources		Р
	a) Inherently limited output		N/A
	b) Impedance limited output		N/A
	c) Regulating network limited output under normal operating and single fault condition		N/A
	d) Overcurrent protective device limited output	(see appended table 2.5)	Р
	Max. output voltage (V), max. output current (A), max. apparent power (VA):	(see appended table 2.5)	_
	Current rating of overcurrent protective device (A) .:	See Table 1.5.1	
	Use of integrated circuit (IC) current limiters		

2.6	Provisions for earthing and bonding		Р
2.6.1	Protective earthing	Class I appliance inlet terminal provided as protective earthing terminal, and accessible metal plate is connected to earthed metal fire enclosure. The test of 2.6.3.4 complied.	Ρ
2.6.2	Functional earthing	Functional earthing in the secondary circuit is accessible at the VGA connector and separated from the primary by reinforced insulation.	Ρ
	Use of symbol for functional earthing		N/A
2.6.3	Protective earthing and protective bonding conductors		Р
2.6.3.1	General	Appliance inlet used. No power cord provided with the unit.	Р
2.6.3.2	Size of protective earthing conductors	AC inlet used	N/A
	Rated current (A), cross-sectional area (mm ²), AWG		
2.6.3.3	Size of protective bonding conductors	Screws fixing earthed PCB trace to metal chassis for protective bonding.	Р
	Rated current (A), cross-sectional area (mm ²), AWG	Refer to test of appended table 2.6.3.4 only.	

Report No. 17051179 002

Ρ

Page 13 of 45

IEC 60950-1

Clause	Requirement + Test	Result - Remark	Verdic
	Protective current rating (A), cross-sectional area (mm ²), AWG	Refer to test of appended table 2.6.3.4 only.	
2.6.3.4	Resistance of earthing conductors and their terminations; resistance (Ω), voltage drop (V), test current (A), duration (min)	(see appended table 2.6.3.4)	Ρ
2.6.3.5	Colour of insulation	Protective bonding conductor as in 2.6.3 and assembled by printed wiring on power board.	N/A
2.6.4	Terminals	See below	Р
2.6.4.1	General		Р
2.6.4.2	Protective earthing and bonding terminals	The earth terminal of the approved appliance inlet is considered as protective earthing terminal and was evaluated by sub clause 2.6.3.4.	Ρ
	Rated current (A), type, nominal thread diameter (mm)	Evaluation by test. See sub- clause 2.6.3.4.	
2.6.4.3	Separation of the protective earthing conductor from protective bonding conductors	Separated PE and protective bonding conductor used.	Ρ
2.6.5	Integrity of protective earthing	See below	Р
2.6.5.1	Interconnection of equipment	Not depending on interconnection for protective earthing.	Р
2.6.5.2	Components in protective earthing conductors and protective bonding conductors	No switch or overcurrent protective device in protective earthing or bonding conductor	Р
2.6.5.3	Disconnection of protective earth	Appliance inlet used for disconnection of protective earth.	Р
2.6.5.4	Parts that can be removed by an operator	AC inlet with PE terminal used.	Ρ
2.6.5.5	Parts removed during servicing		N/A
2.6.5.6	Corrosion resistance	All safety earthing connections comply with Annex J.	Р
2.6.5.7	Screws for protective bonding	No self-tapping or spaced thread screws are used. For the earth connection to the metal chassis a spring washer and a screw are used.	N/A
2.6.5.8	Reliance on telecommunication network or cable distribution system	No TNV circuit.	N/A

2.9 Electrical insulation

Page 14 of 45

Report No. 17051179 002

	IEC 60950-1				
Clause	Requirement + Test	Result - Remark	Verdict		
2.9.1	Properties of insulating materials	Natural rubber, asbestos or hygroscopic material not used.	Р		
2.9.2	Humidity conditioning	Performed at 40°C, 95% R.H. for 120h by client's request.	Р		
	Relative humidity (%), temperature (°C):	See above.			
2.9.3	Grade of insulation	See above.	Р		
2.9.4	Separation from hazardous voltages	The adequate levels of safety insulation provided and maintained to comply with the requirements of this standard.	Р		
	Method(s) used:	SELV separated from primary by reinforced or double insulation.			

2.10	Clearances, creepage distances and distances through insulation		Р
2.10.1	General	See sub-clauses 2.10.3, 2.10.4 and 2.10.5.	Ρ
2.10.1.1	Frequency	Considered	Р
2.10.1.2	Pollution degrees	2	Р
2.10.1.3	Reduced values for functional insulation	Considered	Р
2.10.1.4	Intervening unconnected conductive parts	Considered	Р
2.10.1.5	Insulation with varying dimensions	Insulation kept homogenous.	N/A
2.10.1.6	Special separation requirements	Not applied.	N/A
2.10.1.7	Insulation in circuits generating starting pulses	No such circuits.	N/A
2.10.2	Determination of working voltage		Р
2.10.2.1	General	The rms and the peak voltage were measured with unit connected to a 240V TN power system. The input neutral and secondary ground were connected during measurement. Pollution Degree 2 and Overvoltage Category II considered.	Ρ
2.10.2.2	RMS working voltage	See table 2.10.2	Р
2.10.2.3	Peak working voltage	See table 2.10.2	Р
2.10.3	Clearances	See below and advantage of annex G is not considered.	Р
2.10.3.1	General	Considered.	Р
2.10.3.2	Mains transient voltages		Р

Page 15 of 45

	IEC 60950-1		
Clause	Requirement + Test	Result - Remark	Verdict
	a) AC mains supply	240V a.c. and Overvoltage Category II	Р
	b) Earthed d.c. mains supplies		N/A
	c) Unearthed d.c. mains supplies		N/A
	d) Battery operation		N/A
2.10.3.3	Clearances in primary circuits	(see appended table 2.10.3 and 2.10.4)	Р
2.10.3.4	Clearances in secondary circuits	Sub-clause 5.3.4 considered.	Р
2.10.3.5	Clearances in circuits having starting pulses		N/A
2.10.3.6	Transients from a.c. mains supply	Normal transient voltage considered (overvoltage category II for primary circuit).	N/A
2.10.3.7	Transients from d.c. mains supply		N/A
2.10.3.8	Transients from telecommunication networks and cable distribution systems		N/A
2.10.3.9	Measurement of transient voltage levels		N/A
	a) Transients from a mains supply		N/A
	For an a.c. mains supply		N/A
	For a d.c. mains supply		N/A
	b) Transients from a telecommunication network :		N/A
2.10.4	Creepage distances		Р
2.10.4.1	General		Р
2.10.4.2	Material group and comparative tracking index		Р
	CTI tests:	Material group IIIb is assumed to be used.	—
2.10.4.3	Minimum creepage distances	(see appended table 2.10.3 and 2.10.4)	Р
2.10.5	Solid insulation		Р
2.10.5.1	General		Р
2.10.5.2	Distances through insulation	(see appended table 2.10.5)	Р
2.10.5.3	Insulating compound as solid insulation	Only inside approved optocoupler.	N/A
2.10.5.4	Semiconductor devices	Approved optocoupler complies to IEC 60747-5-2 and having dti. 0.4mm.	Ρ
2.10.5.5.	Cemented joints	Not applied.	N/A
2.10.5.6	Thin sheet material – General		N/A
2.10.5.7	Separable thin sheet material	Used in transformer T901.	Р

Report No. 17051179 002

Page 16 of 45

IEC 60950-1

Clause	Requirement + Test	Result - Remark	Verdict
	Number of layers (pcs):	3 layers for reinforced insulation.	
2.10.5.8	Non-separable thin sheet material	Not applied for.	N/A
2.10.5.9	Thin sheet material – standard test procedure		N/A
	Electric strength test		
2.10.5.10	Thin sheet material – alternative test procedure		Р
	Electric strength test	(see appended table 5.2)	
2.10.5.11	Insulation in wound components	Approved triple insulated wire used for secondary windings of T901.	Р
2.10.5.12	Wire in wound components		Р
	Working voltage	>71Vpeak.	Р
	a) Basic insulation not under stress		N/A
	b) Basic, supplementary, reinforced insulation:		N/A
	c) Compliance with Annex U:	Approved triple insulated wire used.	Р
	Two wires in contact inside wound component; angle between 45° and 90°	Physical separation provided by teflon tube and insulation type to relieve mechanical stress at the crossover point.	Р
2.10.5.13	Wire with solvent-based enamel in wound components	Not applied.	N/A
	Electric strength test		
	Routine test		N/A
2.10.5.14	Additional insulation in wound components	Not applied.	N/A
	Working voltage		N/A
	- Basic insulation not under stress		N/A
	- Supplementary, reinforced insulation		N/A
2.10.6	Construction of printed boards		Р
2.10.6.1	Uncoated printed boards	(see appended table 2.10.3 and 2.10.4)	Р
2.10.6.2	Coated printed boards	Not applied.	N/A
2.10.6.3	Insulation between conductors on the same inner surface of a printed board	Not multi-layer printed board.	N/A
2.10.6.4	Insulation between conductors on different layers of a printed board	See above.	N/A
	Distance through insulation		N/A
	Number of insulation layers (pcs)		N/A

Page 17 of 45

Clause	Requirement + Test	Result - Remark	Verdict
2.10.7	Component external terminations	Coatings not used over terminations to increase effective clearance and creepage distance.	N/A
2.10.8	Tests on coated printed boards and coated components		N/A
2.10.8.1	Sample preparation and preliminary inspection		N/A
2.10.8.2	Thermal conditioning		N/A
2.10.8.3	Electric strength test		N/A
2.10.8.4	Abrasion resistance test		N/A
2.10.9	Thermal cycling		N/A
2.10.10	Test for Pollution Degree 1 environment and insulating compound	Pollution Degree 2.	N/A
2.10.11	Tests for semiconductor devices and cemented joints	Photo couplers are approved components. No other components applied for.	N/A
2.10.12	Enclosed and sealed parts	No hermetically sealed component.	N/A

4	PHYSICAL REQUIREMENTS		Р
4.1	Stability		Р
	Angle of 10°	Test performed by client's request. The equipment does not overbalance when tilted to 10°	Ρ
	Test force (N):	Equipment is not a floor standing unit.	N/A

4.2	Mechanical strength		Р
4.2.1	General	See below. After tests, unit comply with 2.1.1, 2.6.1, 2.10 and 4.4.1.	Ρ
	Rack-mounted equipment.		N/A
4.2.2	Steady force test, 10 N	Applied on internal components	Р
		No components located such that distances according to 2.10 can be reduced.	
4.2.3	Steady force test, 30 N	Internal metal enclosure used. After tests, unit complies with 2.1.1, 2.6.1, 2.10	Р
4.2.4	Steady force test, 250 N	Test performed on plastic enclosure, no hazardous.	Р

Report No. 17051179 002

Page 18 of 45

IEC 60950-1

Clause	Requirement + Test	Result - Remark	Verdict
4.2.5	Impact test	500g steel ball falls freely from 1.3m on top, back and bottom of plastic enclosure, no access to hazardous parts	Р
	Fall test		N/A
	Swing test		N/A
4.2.6	Drop test; height (mm):		N/A
4.2.7	Stress relief test	70°C, 7 hours, no deformation on all sources of plastic enclosure.	Р
4.2.8	Cathode ray tubes	No CRT	N/A
	Picture tube separately certified:		
4.2.9	High pressure lamps	No high pressure lamps provided.	N/A
4.2.10	Wall or ceiling mounted equipment; force (N) :	An additional force 123.8N for 27 inch models or 92.7 for 23.6 inch models required by client applied downwards through the centre of gravity of the equipment for 1 min after the removal of base. After the test, the equipment was not damaged. (123.8N = 3 x 4.21 x 9.8N) (92.7N = 3 x 3.15 x 9.8N)	Ρ

4.5	Thermal requirements		Р
4.5.1	General		Р
4.5.2	Temperature tests		Р
	Normal load condition per Annex L:	Equipment loaded with rated output current.	
4.5.3	Temperature limits for materials	(see appended table 4.5)	Р
4.5.4	Touch temperature limits	(see appended table 4.5)	Р
4.5.5	Resistance to abnormal heat:	Bobbin materials of all transformers T901 and line chock L9901 are Phenolic that are accepted without further tests.	Ρ

5	ELECTRICAL REQUIREMENTS AND SIMULATED ABNORMAL CONDITIONS		Р
5.1	Touch current and protective conductor current		Р
5.1.1	General	See sub-clauses 5.1.2 to 5.1.6.	Р

Page 19 of 45

Report No. 17051179 002

	IEC 60950-1	-	
Clause	Requirement + Test	Result - Remark	Verdict
5.1.2	Configuration of equipment under test (EUT)	See below.	Р
5.1.2.1	Single connection to an a.c. mains supply	EUT has only one mains connection.	Р
5.1.2.2	Redundant multiple connections to an a.c. mains supply		N/A
5.1.2.3	Simultaneous multiple connections to an a.c. mains supply		N/A
5.1.3	Test circuit	Using figure 5A.	Р
5.1.4	Application of measuring instrument	Using measuring instrument in annex D.	Р
5.1.5	Test procedure		Р
5.1.6	Test measurements	(see appended table 5.1.6)	Р
	Supply voltage (V)		
	Measured touch current (mA)		
	Max. allowed touch current (mA)		
	Measured protective conductor current (mA):		
	Max. allowed protective conductor current (mA):		
5.1.7	Equipment with touch current exceeding 3,5 mA	Touch current does not exceed 3.5mA.	N/A
5.1.7.1	General		N/A
5.1.7.2	Simultaneous multiple connections to the supply		N/A
cable distribution systems and from telecommunication networks		No TNV circuits.	N/A
5.1.8.1	Limitation of the touch current to a telecommunication network or to a cable distribution system		N/A
	Supply voltage (V)		
	Measured touch current (mA)		
	Max. allowed touch current (mA)		
5.1.8.2	Summation of touch currents from telecommunication networks		N/A
	a) EUT with earthed telecommunication ports:		N/A
	b) EUT whose telecommunication ports have no reference to protective earth		N/A

5.2	Electric strength		Р
5.2.1	General	(see appended table 5.2)	Р
5.2.2	Test procedure	(see appended table 5.2)	Р

Report No. 17051179 002

Page 20 of 45

IEC 60950-1

Clause	Requirement + Test	Result - Remark	Verdict

5.3	Abnormal operating and fault conditions		
5.3.1	Protection against overload and abnormal operation	Ventilation openings blocked, output of power supply board overloaded, no unaccepted overheating of parts (see appended table 5.3)	Ρ
5.3.2	Motors	Motors not used.	N/A
5.3.3	Transformers	(see appended Annex C and table 5.3)	Ρ
5.3.4	Functional insulation	By short-circuited, results see appended table 5.3.	Ρ
5.3.5	Electromechanical components	No electromechanical component.	N/A
5.3.6	Audio amplifiers in ITE		N/A
5.3.7	Simulation of faults	(see appended table 5.3.)	Р
5.3.8	Unattended equipment	No such equipment.	N/A
5.3.9	Compliance criteria for abnormal operating and fault conditions		Ρ
5.3.9.1	During the tests	No fire or molten metal occurred and no deformation of enclosure during the tests.	Р
5.3.9.2	After the tests	No reduction of clearance and creepage distance. Electric strength test is made on basic, supplementary and reinforced insulation after test.	Ρ

U	ANNEX U, INSULATED WINDING WIRES FOR USE WITHOUT INTERLEAVED INSULATION (see 2.10.5.4)		Р
		Approved triple insulated wire used.	

Page 21 of 45

Report No. 17051179 002

IEC 60950-1

Clause Requirement + Test

Result - Remark

Verdict

1.5.1 TA	BLE: List of critic	al components			Р
Object/part No.	Manufacturer/ trademark	Type/model	Technical data	Standard (Edition / year)	Mark(s) of conformity ¹)
LCD Panel with LED backlight for 23.6 inch models	CHI MEI	M236H*-*** (*can be 0~9, A~Z, blank for marking purpose)	23.6 inch panel with LED backlight The declared power consumption is 20.75W and backlight input voltage is 51.2V in specification.	IEC 60950-1	Tested in equipment
	IVO	M236MWF* (*can be 0~9, A~Z, blank for marking purpose)	23.6 inch panel with LED backlight The declared power consumption is 18.95W and backlight input voltage is 28.8V in specification.	IEC 60950-1	Tested in equipment
	BOE	HM236W**-*** (*can be 0~9, A~Z, blank for marking purpose)	23.6 inch panel with LED backlight The declared power consumption is 20.076W and backlight input voltage is 46.5V in specification.	IEC 60950-1	Tested in equipment
	TPV	TPM236** (*can be 0~9, A~Z, blank for marking purpose)	23.6 inch panel with LED backlight The declared power consumption is 17.7W and backlight input voltage is 31.5V in specification.	IEC 60950-1	Tested in equipment

Page 22 of 45

Report No. 17051179 002

Result - Remark

|--|

Re	quirement + Test	

Verdict

<u> </u>	-				
	TPV	TPM236WF* (*can be 0~9, A~Z, blank for marking purpose)	23.6 inch panel with LED backlight The declared power consumption is 20.4W and backlight input voltage is 35.2V in specification.	IEC 60950-1	Tested in equipment
	CHI MEI	M236H**-*** (*can be 0~9, A~Z, blank for marking purpose)	23.6 inch panel with LED backlight The declared power consumption is 20.2W and backlight input voltage is 57.6V in specification.	IEC 60950-1	Tested in equipment
	BOE	HR236WU*-*** (*can be 0~9, A~Z, blank for marking purpose)	23.6 inch panel with LED backlight The declared power consumption is 22.8W and backlight input voltage is 44.8V in specification.	IEC 60950-1	Tested in equipment
	SAMSUNG	LTM236FL** (*can be 0~9, A~Z, blank for marking purpose)	23.6 inch panel with LED backlight The declared power consumption is 23.83W and backlight input voltage is 34.1V in specification.	IEC 60950-1	Tested in equipment
Metal enclosure (except part under power board)	interchangeable	interchangeable	Metal thickness: min. 0.4mm		
Metal enclosure (under power board)	interchangeable	interchangeable	Metal thickness: min. 0.81mm		
РСВ	interchangeable	interchangeable	V-1 or better, min. 105°C	UL 94	UL

Clause

Page 23 of 45

Report No. 17051179 002

			IEC 60)950-1				1	
Clause	Rec	uirement + Test		Resu		t - Remark		Verdict	
Mylar sheet between power board and metal enclosure type B		interchangeable	interchangeable	min. 0.25mm thickness, V-2, 105°C		UL 94	UL		
Mylar sheet for metal enclosure type B (used to cover the side opening of metal enclosure)		interchangeable	interchangeable	min. 0.4mm thickness, V-1 or better, 105°C, adhered to metal enclosure by below adhesive or glue			UL	UL	
Power Su	pply v	vith LED driver bo	oard, type No. 715	G7775 by T	PV				
AC-Inlet (CN901)		Inalways Corporation Co., Ltd.	0707-1, 0711-2, 0714	10A, 250V,	70°C	IEC/ EN 60320-1, UL498	VDI	E, UL	
		Zhang Jia Gang Hua Jie Electronics Co., Ltd.	SA-4S SA-4S-1	10A, 250V, 70°C IEC/ EN 60320-1, UL498		VD	E, UL		
		Rong Feng Industrial Co., Ltd.	SS-120, SS-7B	10A, 250V, 70°C IEC/ EN 60320-1, UL498		VDI	E, UL		
		DELIKANG/ Douling	CDJ-3 CDJ-3-1	10A, 250V, 70°C IEC/ EN 60320-1, UL498		VD	E, UL		
		Solteam Electronics Co., Ltd.	ST-01	10A, 250V,	70°C	IEC/ EN 60320-1, UL498	VDI	E, UL	
		TECX	TU-301-AP, TU-301-S, TU-301-SP, TU-301-A	10A, 250V,	70°C	IEC/ EN 60320-1, UL498	VD	E, UL	
		Yueqing Hongchang	DB-14	10A, 250V,	70°C	IEC/ EN 60320-1, UL498	VDI	E, UL	
		Yueqing Hongchang	DB-6	15A, 250Va	IC	IEC/ EN 60320-1, UL498	VDI	E, UL	
		TECX	TU-301 series	10A, 250V,	70°C	IEC/ EN 60320-1,	VD	=	
Power Swi (SW901) (optional)	itch	Solteam	OR-L	VDE: 6A, 250Vac; UL:10A, 12	5Vac	IEC/EN 61058-1, ANSI/UL 1054	VDI	E, UL	
		Rong Feng	RF-1003	VDE: 10(4)/ 250Vac; UL: 10A, 25		IEC/EN 61058-1, ANSI/UL 1054	VD	E, UL	

Page 24 of 45

Report No. 17051179 002

		Faye 24	60950-1		Report No.		
Clause I	Requirement + Test			Resu	lt - Remark		Verdict
	vequirement + rest			Resu			Vertilit
	Solteam	MR-22	ENEC: 12(4 250Vac; UL: 12A, 125/250Vac		IEC/EN 61058-1, ANSI/UL 1054	ENI	EC, UL
	Solteam	MR-21 series	ENEC: 12(4 250Vac; UL: 12A, 125/250Vac		IEC/EN 61058-1, ANSI/UL 1054	ENI	EC, UL
Fuse (F9901) primary; F901 for L.P.S +5V		MET, MST, PTU	T4AL, 250∖	/ac	IEC/ EN 60127-1, IEC/ EN 60127-3, UL 248	VDI	Ξ, UL
	Littelfuse, Inc. Wickmann	392, 382-series	T4AL, 250∖	/ac	IEC/ EN 60127-1, IEC/ EN 60127-3, UL 248	VDI	E, UL
	Cooper Bussmann	SR-5, SS-5	T4AL, 250∖	/ac	IEC/ EN 60127-1, IEC/ EN 60127-3, UL 248	VDI	E, UL
	Ever Island Electric Co. Itd and Walter electric	2000, 2010 serie(s)	T4AL, 250∖	/ac	IEC/ EN 60127-1, IEC/ EN 60127-3, UL 248	VDI	Ξ, UL
Fuse (F801 fo L.P.S +16V)	or Conquer	MET, MST, PTU	T2AL, 250Vac		IEC/ EN 60127-1, IEC/ EN 60127-3, UL 248	VDI	E, UL
	Littelfuse, Inc. Wickmann	392, 382-series	T2AL, 250∖	/ac	IEC/ EN 60127-1, IEC/ EN 60127-3, UL 248	VDI	E, UL
	Cooper Bussmann	SR-5, SS-5	T2AL, 250∖	/ac	IEC/ EN 60127-1, IEC/ EN 60127-3, UL 248	VDI	E, UL
	Ever Island Electric Co. Itd and Walter electric	2000, 2010 serie(s)	T2AL, 250∖	/ac	IEC/ EN 60127-1, IEC/ EN 60127-3, UL 248	VDI	Ξ, UL
Y- Capacitor (C9901, C990	·	AC, AH	Max. 4700p 250Vac, 85		IEC/EN 60384-14, UL 60384-14	VDI	E, UL
(Y1 or Y2 type (optional)	e) Yinan Don	CT81	Max. 4700p 250Vac, 85		IEC/EN 60384-14, UL 60384-14	VDI	E, UL
	Haohua	CT7	Max. 4700p 250Vac, 85		IEC/EN 60384-14, UL 60384-14	VDI	E, UL
	Wansheng	CT7	Max. 4700p 250Vac, 85		IEC/EN 60384-14, UL 60384-14	VDI	E, UL
	TDK	CS, CD	Max. 4700p 250Vac, 85		IEC/EN 60384-14, UL 60384-14	VDI	E, UL
	Samwha	SD	Max. 4700p 250Vac, 85		IEC/EN 60384-14, UL 60384-14	VDI	E, UL

Page 25 of 45

Report No. 17051179 002

Page 25 of 45 Report No. 17051179 002							
		IEC 6	0950-1				
Clause Red	quirement + Test		Resi	ult - Remark	Verdict		
	Murata	КН, КХ	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14, UL 60384-14	VDE, UL		
	Matsushita	NS-A, NS-B	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14, UL 60384-14	VDE, UL		
	JYA-NAY	JY, JN	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14, UL 60384-14	VDE, UL		
	Success	SE, SB	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14, UL 60384-14	VDE, UL		
	Hongming	F	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14, UL 60384-14	VDE, UL		
Y- Capacitor (C9904)	Walsin	АН	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
Y1 type (optional)	Yinan Don's	CT81	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
	Haohua	CT7	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
	Wansheng	CT7	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
	ТДК	CD	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
	Murata	кх	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
	Matsushita	NS-A	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
	JYA-NAY	JN	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
	Success	SE, SB	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
	Hongming	F	Max. 4700pF, 250Vac, 85°C	IEC/EN 60384-14 UL 60384-14	VDE, UL		
X-Capacitor (C9903) (X1 or X2 type)	Ultra Tech Xiphi	HQX	Max. 0.47µF, min. 275Vac, 85°C	IEC/EN 60384-14, UL 60384-14	VDE, UL		
(optional)	Hua Jung	МКР	Max. 0.47µF, min. 275Vac, 85°C	IEC/EN 60384-14, UL 60384-14	ENEC (Semko), UL		
	Faratronic	MKP62	Max. 0.47µF, min. 275Vac, 85°C	IEC/EN 60384-14, UL 60384-14	VDE, UL		
	Europtronic	MPX	Max. 0.47µF, min. 275Vac, 85°C	IEC/EN 60384-14, UL 60384-14	VDE, UL		

Page 26 of 45

Report No. 17051179 002

Page 26 of 45 Report No. 17051179 002							
		IEC 6	0950-1				
Clause F	Requirement + Test			Resul	t - Remark		Verdict
	Europtronic	MPX2	Max. 0.47µ min. 275Va 85°C		IEC/EN 60384-14, UL 60384-14	VD	E, UL
	Liow Gu	GS-L	Max. 0.47µ min. 275Va 85°C		IEC/EN 60384-14, UL 60384-14	VD	E, UL
	EPCOS	B3292#	Max. 0.47µ min. 275Va 85°C		IEC/EN 60384-14, UL 60384-14	VD	E, UL
	Arcotronics	R.46	Max. 0.47µ min. 275Va 85°C		IEC/EN 60384-14, UL 60384-14	ENE UL	EC(IMQ),
	ZHUHAI SUNG HO ELECTRONICS CO LTD	CMPP	Max. 0.47µ min. 275Va 85°C		IEC/EN 60384-14, UL 60384-14	VD	E, UL
Photo Couple (U902)	r Sharp	PC123	Di=0.7mm, int.cr= ther cycling ³⁾ , ext.cr=8.0r min. 3000\ 100°C	mal nm,	DIN/EN 60747-5-2, IEC/EN 60950-1, UL 1577	VDE UL, Sen Fim Ner	nko, ko,
	Vishay Semiconductor	TCET1103	Di=0.6mm, int.cr= ther cycling ³⁾ , ext.cr=8.4r min. 3000\ 100°C	mal nm,	DIN/EN 60747-5-2, IEC/EN 60950-1, UL 1577	VDE UL, Sen Fim	nko,
	Everlight Electronics Co., Ltd.	EL817	Di=0.5mm, int.cr=6.0m ext.cr=7.7r min. 3000\ 100°C	nm, nm,	DIN/EN 60747-5-2, IEC/EN 60950-1, UL 1577	VDE UL, Sen Fim Ner	nko, ko,
	Everlight Electronics Co., Ltd.	EL1013	Di=0.4mm, int.cr=therr cycling ³⁾ , ext.cr=8.0r min. 3000\ 100°C	nal nm,	DIN/EN 60747-5-2, IEC/EN 60950-1, UL 1577	VDE UL, Sen	,
	Lite-on	LTV-817	Di=0.4mm, int.cr= ther cycling ³⁾ , ext.cr=8.0r min. 3000\ 100°C	mal n,	DIN/EN 60747-5-2, IEC/EN 60950-1, UL 1577	VD	E, UL

Page 27 of 45

Report No. 17051179 002

IEC 60950-1

Clause Requirement + Test

Result - Remark

Verdict

Clause Requirement + rest			Result - Remark		
	Renesas	PS2561-1 PS2561L-1 PS2561L1-1 PS2561L2-1 PS2561DL1-1	Di=0.4mm, int.cr=thermal cycling ³⁾ , ext.cr=8.0mm min. 3000Vac 100°C	IEC/EN 60950-1, UL 1577	VDE, UL, Fimko, Nemko
	TOSHIBA	TLP421F	Di=0.4mm, int.cr=thermal cycling ³⁾ , ext.cr=8.0mm min. 3000Vac 100°C	IEC/EN 60950-1, UL 1577	VDE, UL, Semko, Fimko
	TOSHIBA	TLP781F TLP781	Di=0.4mm, int.cr=thermal cycling ³⁾ , ext.cr=8.0mm min. 3000Vac 100°C	IEC/EN 60950-1, UL 1577	VDE, UL, Semko, Fimko
Bridging Diode (BD9902)	interchangeable	interchangeable	Min. 2.0A, min. 600Vac		
Ripple Capacitor (C901)	interchangeable	interchangeable	45-150µF, min. 450 V, min. 105 °C		
Transistor (Q901)	interchangeable	interchangeable	Min. 600V, min. 6.0A		
Thermistors (TH9901) (Optional)	interchangeable	interchangeable	Min. 0.2Ω at 25°C, min. 2A		
Current sensor resistor (R914)	interchangeable	interchangeable	Min 0.22Ω, 2V	N	
Bleeder Resistor (R9901, R9902, R9903)	interchangeable	SMD type	Max. 680 koh min. 1/4 W (three in serie located after fuse)		
Line Choke (L9901)	ASET	73G174-241-X	105°C		Tested in equipment
(optional)	CHENPING	73G174-241-CP	105°C		Tested in equipment
	YUVA	73G174-241-N	105°C		Tested in equipment
	Dadon	73G174-241-H	105°C		Tested in equipment
Transformer (T901) (Alt.)	TAICHANG	380GL32P542S	Class B	according to	Accepted by TÜV Rheinland

Page 28 of 45

Report No. 17051179 002

	IEC 609	50-1	
Clause	Requirement + Test	Result - Remark	Verdict

Bobbin	Sumitomo	PM-9820	V-0, Phenolic, 150°C	UL 94	UL
Triple insulation wire	GREAT LEOFLON	TRW(B)	Max.130°C	IEC/EN 60950-1, VDE0805 Teil1, UL 2353	UL, VDE
Teflon tube	GREAT HOLDING	TFL	200°C	UL 224	UL
Transformer (T901) (Alt.)	Channelon	380GL32P542H	Class B	Applicable part according to IEC60950-1 and IEC 60085	Accepted by TÜV Rheinland
Bobbin	Sumitomo	PM-9820	V-0, Phenolic, 150°C	UL 94	UL
Triple insulation wire	COSMOLINK	TIW-M	Max.130°C	IEC/EN 60950-1, VDE0805 Teil1, UL 2353	UL, VDE
Teflon tube	GREAT HOLDING	TFL	200°C	UL 224	UL
Transformer (T901) (Alt.)	LI TAI	380GL32P542L	Class B	Applicable part according to IEC60950-1 and IEC 60085	Accepted by TÜV Rheinland
Bobbin	Sumitomo	PM-9820	V-0, Phenolic, 150°C	UL 94	UL
Triple insulation wire	COSMOLINK	TIW-M	Max.130°C	IEC/EN 60950-1, VDE0805 Teil1, UL 2353	UL, VDE
Teflon tube	GREAT HOLDING	TFL	200°C	UL 224	UL

Supplementary information:

- 1. Provided evidence ensures the agreed level of compliance.
- 2. 'Di' means distance through insulation, 'int.' Means internal distance of creepage and 'ext.' Means external distance of creepage.
- There is no any internal creepage distance. Test according to IEC60950-1:2001, cl. 2.10.8 (same as requirement in IEC60950-1:2005, cl. 2.10.9) has been carried out ten times for the components at 100°C / 25°C / 0°C / 25°C. Humidity treatment of 48 hours as well as electric strength tests at 3000V / 1 minute was carried out to the component after thermal cycling test.
- 4. All sources of photo coupler were certified according to DIN EN60747-5-2 which in compliance with the requirements and provisions of IEC 60747-5-5.
- 5. All sources of photo coupler were in compliance with CTL DSH 759 decision.
- 6. All sources of transformer were checked with same construction.

Page 29 of 45

Report No. 17051179 002

IEC 60950-1

Result - Remark

Verdict

1.6.2	TABLE: Electi	rical data (in	normal condit	ions)		Р
Fuse #	U (V)	I (A)	Irated (A)	P (W)	Ifuse (A)	Condition/status
For 27 inch	n models			I		
Tested wit	h power board	715G7775, n	nain board 715	ی G5436 and	banel M270	DAN**** (AUO)
VGA mode						
F9901	90V/50Hz	0.45		23.4	0.45	Normal load condition
F9901	90V/60Hz	0.45		23.4	0.45	Normal load condition
F9901	100V/50Hz	0.41	1.5	23.3	0.41	Normal load condition
F9901	100V/60Hz	0.41	1.5	23.2	0.41	Normal load condition
F9901	240V/50Hz	0.24	1.5	23.1	0.24	Normal load condition
F9901	240V/60Hz	0.24	1.5	23.1	0.24	Normal load condition
F9901	264V/50Hz	0.22		23.1	0.22	Normal load condition
F9901	264V/60Hz	0.22		23.1	0.22	Normal load condition
DVI mode						
F9901	90V/50Hz	0.45		23.9	0.45	Normal load condition
F9901	90V/60Hz	0.45		23.8	0.45	Normal load condition
F9901	100V/50Hz	0.41	1.5	23.8	0.41	Normal load condition
F9901	100V/60Hz	0.41	1.5	23.8	0.41	Normal load condition
F9901	240V/50Hz	0.23	1.5	23.7	0.23	Normal load condition
F9901	240V/60Hz	0.23	1.5	23.6	0.23	Normal load condition
F9901	264V/50Hz	0.22		23.6	0.22	Normal load condition
F9901	264V/60Hz	0.22		23.6	0.22	Normal load condition
HDMI mode	9					
F9901	90V/50Hz	0.48		25.5	0.48	Normal load condition
F9901	90V/60Hz	0.48		25.4	0.48	Normal load condition
F9901	100V/50Hz	0.45	1.5	25.3	0.45	Normal load condition
F9901	100V/60Hz	0.45	1.5	25.3	0.45	Normal load condition
F9901	240V/50Hz	0.26	1.5	25.4	0.26	Normal load condition
F9901	240V/60Hz	0.26	1.5	25.3	0.26	Normal load condition
F9901	264V/50Hz	0.24		25.4	0.24	Normal load condition
F9901	264V/60Hz	0.24		25.3	0.24	Normal load condition
Tested wit	h power board '	715G7775, n	nain board 715	G7612 and J	banel M270	DAN**** (AUO)
VGA mode						
F9901	90V/50Hz	0.43		23.5	0.43	Normal load condition

TRF No. IEC60950_1F

Clause

Requirement + Test

			Page 30 of	45		Report No. 170	51179 002
			IEC 6095	50-1			
Clause	Requirement +	Test		F	Result - Rem	ark	Verdict
F9901	90V/60Hz	0.43		23.4	0.43	Normal load con	dition
F9901	100V/50Hz	0.40	1.5	23.4	0.40	Normal load con	dition
F9901	100V/60Hz	0.39	1.5	23.4	0.39	Normal load con	dition
F9901	240V/50Hz	0.23	1.5	23.3	0.23	Normal load con	dition
F9901	240V/60Hz	0.22	1.5	23.3	0.22	Normal load con	dition
F9901	264V/50Hz	0.21		23.2	0.21	Normal load con	dition
F9901	264V/60Hz	0.21		23.2	0.21	Normal load con	dition
DisplayPo	rt mode			1	1	1	
F9901	90V/50Hz	0.50		27.1	0.50	Normal load con	dition
F9901	90V/60Hz	0.50		27.0	0.50	Normal load con	dition
F9901	100V/50Hz	0.47	1.5	26.7	0.47	Normal load con	dition
F9901	100V/60Hz	0.47	1.5	26.6	0.47	Normal load con	dition
F9901	240V/50Hz	0.27	1.5	26.3	0.27	Normal load con	dition
F9901	240V/60Hz	0.27	1.5	26.3	0.27	Normal load con	dition
F9901	264V/50Hz	0.25		26.2	0.25	Normal load con	dition
F9901	264V/60Hz	0.25		26.1	0.25	Normal load con	dition
HDMI mod	e						
F9901	90V/50Hz	0.54		28.7	0.54	Normal load con	dition
F9901	90V/60Hz	0.54		28.6	0.54	Normal load con	dition
F9901	100V/50Hz	0.50	1.5	28.4	0.50	Normal load con	dition
F9901	100V/60Hz	0.50	1.5	28.5	0.50	Normal load con	dition
F9901	240V/50Hz	0.29	1.5	27.8	0.29	Normal load con	dition
F9901	240V/60Hz	0.29	1.5	27.5	0.29	Normal load con	dition
F9901	264V/50Hz	0.27		27.9	0.27	Normal load con	dition
F9901	264V/60Hz	0.27		27.8	0.27	Normal load con	dition
For 23.6 in	ich models						
Tested wit	h power board	715G7775, n	nain board 715	G5436 and	panel LTM	236FL** (SAMSU	NG)
VGA mode)						
F9901	90V/50Hz	0.39		20.7	0.39	Normal load con	dition
F9901	90V/60Hz	0.39		20.6	0.39	Normal load con	dition
F9901	100V/50Hz	0.36	1.5	20.6	0.36	Normal load con	dition
F9901	100V/60Hz	0.36	1.5	20.6	0.36	Normal load con	dition
F9901	240V/50Hz	0.20	1.5	20.5	0.20	Normal load con	dition
F9901	240V/60Hz	0.20	1.5	20.4	0.20	Normal load con	dition

Page 31 of 45

Report No. 17051179 002

IEC 60950-1

			IEC 6093	00-1			
Clause	Requirement +	Test		F	Result - Rem	ark	Verdict
F9901	264V/50Hz	0.19		20.3	0.19	Normal load co	ndition
F9901	264V/60Hz	0.19		20.3	0.19	Normal load co	ndition
DVI mode	I	I		1		1	
F9901	90V/50Hz	0.39		21.1	0.39	Normal load co	ndition
F9901	90V/60Hz	0.39		21.0	0.39	Normal load co	ndition
F9901	100V/50Hz	0.37	1.5	20.9	0.37	Normal load co	ndition
F9901	100V/60Hz	0.36	1.5	21.0	0.36	Normal load co	ndition
F9901	240V/50Hz	0.21	1.5	21.0	0.21	Normal load co	ndition
F9901	240V/60Hz	0.20	1.5	20.9	0.20	Normal load co	ndition
F9901	264V/50Hz	0.20		20.9	0.20	Normal load co	ndition
F9901	264V/60Hz	0.20		20.8	0.20	Normal load co	ndition
HDMI mod	le			•			
F9901	90V/50Hz	0.41		23.4	0.41	Normal load co	ndition
F9901	90V/60Hz	0.41		23.4	0.41	Normal load co	ndition
F9901	100V/50Hz	0.38	1.5	23.3	0.38	Normal load co	ndition
F9901	100V/60Hz	0.38	1.5	23.2	0.38	Normal load co	ndition
F9901	240V/50Hz	0.22	1.5	23.2	0.22	Normal load co	ndition
F9901	240V/60Hz	0.22	1.5	23.2	0.22	Normal load co	ndition
F9901	264V/50Hz	0.20		23.1	0.20	Normal load co	ndition
F9901	264V/60Hz	0.20		23.1	0.20	Normal load co	ndition
Tested wit	th power board	715G7775, n	nain board 715	G76970 an	d panel LT	M236FL** (SAMS	UNG)
VGA mode)						
F9901	90V/50Hz	0.38		19.8	0.38	Normal load co	ndition
F9901	90V/60Hz	0.37		19.7	0.37	Normal load co	ndition
F9901	100V/50Hz	0.35	1.5	19.7	0.35	Normal load co	ndition
F9901	100V/60Hz	0.35	1.5	19.6	0.35	Normal load co	ndition
F9901	240V/50Hz	0.20	1.5	19.6	0.20	Normal load co	ndition
F9901	240V/60Hz	0.20	1.5	19.5	0.20	Normal load co	ndition
F9901	264V/50Hz	0.19		19.6	0.19	Normal load co	ndition
F9901	264V/60Hz	0.19		19.5	0.19	Normal load cor	ndition
DisplayPo	rt mode						
F9901	90V/50Hz	0.38		20.1	0.38	Normal load co	ndition
F9901	90V/60Hz	0.38		20.1	0.38	Normal load co	ndition
F9901	100V/50Hz	0.35	1.5	20.1	0.35	Normal load co	ndition

Page 32 of 45

Report No. 17051179 002

IEC 60950-1									
Clause	Requirement + Test				Result - Remark		Verdict		
F9901	100V/60Hz	0.35	1.5	20.0	0.35	Normal load con	dition		
F9901	240V/50Hz	0.20	1.5	20.1	0.20	Normal load condition			
F9901	240V/60Hz	0.20	1.5	20.0	0.20	Normal load condition			
F9901	264V/50Hz	0.19		20.1	0.19	Normal load condition			
F9901	264V/60Hz	0.19		20.1	0.19	Normal load condition			
HDMI mod	e			•		·			
F9901	90V/50Hz	0.39		20.6	0.39	Normal load con	dition		
F9901	90V/60Hz	0.39		20.6	0.39	Normal load condition			
F9901	100V/50Hz	0.35	1.5	20.5	0.35	Normal load con	dition		
F9901	100V/60Hz	0.35	1.5	20.5	0.35	Normal load condition			
F9901	240V/50Hz	0.20	1.5	20.3	0.20	Normal load condition			
F9901	240V/60Hz	0.20	1.5	20.3	0.20	Normal load condition			
F9901	264V/50Hz	0.19		20.2	0.19	Normal load condition			
F9901	264V/60Hz	0.19		20.1	0.19	Normal load condition			

Note(s):

1. Maximum normal load: maximum brightness, maximum contrast, full white screen; speakers were loaded with 1KHz sinusoidal signal and turned to maximum volume; which was considered as maximum output power.

2. Panels mentioned above chosen for the test, due to the higher power consumption specified in panel spec than any other panel of same size.

TABLE: max. V, A, VA test						
d)	Current (rated) (A)	Voltage (max.) (V)	Current (max.) (A)	VA (max.) (VA)		
		16.3	5.2	47		
+5V ^{2.}		5.3	10	44		
		d) Current (rated) (A) 	d) Current (rated) Voltage (max.) (A) (V) 16.3	d) Current (rated) Voltage (max.) (V) (A) 16.3 5.2		

Note(s): Test voltage is 264Vac, 60Hz

1. Test on the circuit after fuse F801 on power board.

2. Test on the circuit after fuse F901 on power board.

2.1.1.7	TABLE: discharge test					
Condition		τ calculated (s)	τ measured (s)	t u \rightarrow 0V (s)	Comments	
System on (with fuse in, L-N)		0.96	0.77		$U_{\rm OC}$ = 381 Vpk, 37% of $U_{\rm OC}$ = 141 Vpk,	
Page	33	of	45			
------	----	----	----			
------	----	----	----			

Report No. 17051179 002

IEC 60950-1

		IEC 00930-1	
Clause	Requirement + Test		Result - Remark

Verdict

Supplementary information:

1. Overall capacity: (C9903=0.47 μ F), Discharge resistor: 2.04M Ω (R9901=R9902=R9903=680k Ω); 2. Supplied with 264V/60Hz and 90V/60Hz. And worse test result was recorded.

2.2	TABLE: Hazardous voltage me	easurement			Р
Componen	t (measured between)		max. voltage (V) (normal operation)		
		V peak	V d.c.		
T901 Pin 6,	7 – Pin 8,9	21.3			
T901 Pin 10) – Pin 8,9	61.0			
After R915		59.7		R915	
After C912		31.0		C912	
After C913/D908			16.3	C913/D908	
After L801			30.7		
Converter of	circuit to Earth		41.6		
Fault test p component	erformed on voltage limiting s	Voltage measured (V) in SELV circuits (V peak or V d.c.)			
R915 (s-c)		16.2V (for +16V output)			
C912 (s-c)			16.3V (for +16V output)		
C913 (s-c)		16.3V (for +16V output)			
D908 (s-c)			0V (for +16V output)		
Supplemen	tary information: Input Voltage is 2	240Vac 60Hz			

Supplementary information: Input Voltage is 240Vac, 60Hz

2.4.2	TABLE: limited current circuit measurement						Р
Location		Voltage (V)	Current (mA)	Freq. (kHz)	Limit (mA)	Comments	
bridging Y1 (C9904)	capacitor		0.52		0.7		
Suppleme	Supplementary information:						
1. Measu	1. Measured with figure D.1 instrument.						

Page 34 of 45

Report No. 17051179 002

	IEC 60950-1		
Clause	Requirement + Test	Result - Remark	Verdict

2.5	TABLE: Limited	power sources				Р
Circuit outp	out tested: +16V out	put				·
Note: Meas	sured Uoc (V) with a	Il load circuits dis	connected:			
		Uoc (V)	DC (V) I _{sc} (A) VA			
			Meas.	Limit	Meas.	Limit
Normal condition		16.3	5.2	61.3 (20)	47	250
Circuit outp	out tested: +5V outp	ut		· · ·		
Note: Meas	sured Uoc (V) with a	II load circuits dis	connected:			
		Uoc (V)	I _{sc} (A) VA			A
			Meas.	Limit	Meas.	Limit
Normalian	dition	5.3	10	188.7 (40)	44	250

1. Input Voltage is 240Vac, 60Hz. Sc=Short circuit, Oc=Open circuit.

2. +16V and +5V outputs with fuses F801, F901 that will break the circuit within 120 s with a current equal to 210%. Current limit of table 2C reduced to breaking capacity of the fuse (20A or 40A).

2.6.3.4	TABLE: ground cont	tinue test		Р
Location		Resistance measured (m Ω)	Comments	
PE terminal metal enclos	of AC inlet to internal sure	5.0	Test with 32A, 2 minutes	
PE terminal metal enclos	of AC inlet to internal sure	5.0	Test with 40A, 2 minutes	
	of AC inlet to)9/C9910 secondary	6.1	Test with 32A, 2 minutes	
	of AC inlet to)9/C9910 secondary	6.3	Test with 40A, 2 minutes	
Note(s):		I	1	

2.10.2	Table: working voltage	Table: working voltage measurement				
Location		Peak voltage (V)	RMS voltage (V)	Comments		
T901: Pin 1	to pin 6,7	378	179			
T901: Pin 1	to pin 8,9	388	177			
T901: Pin 1	to pin 10	350	177			
T901: Pin 2	to pin 6,7	353	179			
T901: Pin 2	to pin 8,9	345	178			

TRF No. IEC60950_1F

Page 35 of 45

Report No. 17051179 002

		1 490 00	01 10	. top	
		IEC 6	0950-1		
Clause	Requirement + Test			Result - Remark	Verdict
T001 · Din	2 to pin 10	375	177	,	
T901: Pin	4 to pin 6,7	366	234		
T901: Pin	4 to pin 8,9	342	230		
T901: Pin	4 to pin 10	410	248	6	
T901: Pin	5 to pin 6,7	488	247	,	
T901: Pin	5 to pin 8,9	500	260	Max	Vrms & Vpeak
T901: Pin	5 to pin 10	490	258		
U902 Pin	1-3	353	184		

348

348

350

341

182

182

181 212

2.10.3 and TABLE: clearanc 2.10.4	e and creep	age distance	e measureme	ents		Р
Clearance cl and creepage distance dcr at/of:	U p (V)	U r.m.s. (V)	Required cl (mm)	cl (mm)	Required dcr (mm)	dcr (mm)
Functional:						
Under fuse (F9901) ^{1.}	420	250	2.3	2.7	2.5	4.0
Before fuse (between L-N)	420	250	2.3	4.1	2.5	6.6
Basic / supplementary:					· · ·	
Line-GND ^{1.}	420	250	3.0	3.0 ⁷⁾	3.0	4.2
Neutral-GND ^{1.}	420	250	3.0	3.0 ⁷⁾	3.0	4.2
Under C9902 ^{1.}	420	250	3.0	7.9	3.0	7.9
Under C9901	420	250	3.0	7.3	3.0	7.3
Primary component C823 to metal enclosure	420	250	3.0	5.1	3.0	5.1
Primary component (main transformer) to metal enclosure	500	260	3.3	11.3	3.3	11.3
Primary component to panel plate	500	260	3.3	9.3	3.3	9.3
Reinforced:						
Under T9101	500	260	6.6	18.0	6.6	18.0
Under C9904	420	250	6.0	7.6	6.0	7.6

TRF No. IEC60950_1F

U902 Pin 1-4

U902 Pin 2-3

U902 Pin 2-4

C9904 Pin 1-2

Note(s): Input Voltage is 240Vac, 60Hz

Report No. 17051179 002

IEC 60950-1

Clause	Requirement + Test	Result - Remark	Verdict

U9401 primary pin to U9401 secondary pin (trace side)	420	250	6.0	8.3	6.0	8.3

Supplementary information:

1. There is one slot measured 1mm width.

- 2. Core of main transformer T901 consider as primary.
- 3. One mylar sheet is fixed between primary components L9901, HS902 and metal enclosure to fulfill the requirement for basic insulation.
- 4. Glued component: C901.
- 5. Considered altitude correction factor 1.48 for clearances for an altitude of 5000m.
- 6. For clearance and creepage that did not describe above are far larger than limit above.
- 7. Same test result after repeat two more measurements on same position.

2.10.5	TABLE: Distance through insulation measurements					
Distance th	rough insulation DTI at/of:	U peak (V)	U rms (V)	Test voltage (V)	Required DTI (mm)	DTI (mm)
Photo coup	er (reinforced insulation)	420	250	3000	0.4	1.
Supplemen	tary information:	·				
4	and common of course and common	ا ما اما ما	F 4			

1. For approved component source see appended table 1.5.1.

4.5	TABLE: Thermal requirements			Р				
	Supply voltage (V)	90V/60Hz	264V/60Hz					
	Ambient T _{min} (°C)							
	Ambient T _{max} (°C)							
Maximum measured temperature T of T (°C) part/at:				Allowed T _{max} (°C)				
	Tested with power board 715G7775, main board 715G7612 and panel M270DAN**** (AUO), HDMI mode							
At horizo	ntal orientation							
Line pin	of AC Inlet CN901 (on power board)	31.7	31.0	49.3				
Switch b	ody(on power board)	31.5 30.1		59.3				
C9901 b	ody (on power board)	31.3 30.5		64.3				
C9903 (d	on power board)	33.4 32.3		64.3				
C9904 b	ody (on power board)	34.3	33.7	64.3				
L9901 cc	bil (on power board)	41.5	40.5	84.3				
PCB near BD9902 (on power board)		36.1	35.6	84.3				
U902 Body		39.7	38.5	79.3				

TRF No. IEC60950_1F

	Pa	age 37 of 45	Report No. 170	51179 002
		IEC 60950-1		
Clause	Requirement + Test	Result	- Remark	Verdict
C901 (on	power board)	35.3	34.5	84.3
T901 coil (on power board)		56.4	55.7	89.3
T901 core	e (on power board)	53.9	52.5	89.3
PCB near Q901 (on power board)		43.3	42.7	84.3
PCB near Main IC (main board)		41.9	41.3	84.3
PCB near L801 (on power board)		39.3	37.7	84.3
Metal enc	losure	31.8	30.6	54.3
Plastic en	closure inside near T901	30.1	28.9	
Plastic enclosure outside		26.9	25.8	74.3
Panel surf	face	33.6	32.7	74.3
Ambient		19.7	19.3	
Tested w HDMI mo	ith power board 715G7775, main b de	oard 715G5436 and pane	I LTM236FL** (SAMSU	NG),
At horizon	tal orientation			
Line pin o	f AC Inlet CN901 (on power board)	30.7	29.6	52.5
Switch bo	dy(on power board)	30.5	29.3	62.5
C9901 bo	dy (on power board)	31.7	30.1	67.5
C9903 (or	n power board)	32.7	31.5	67.5
C9904 bo	dy (on power board)	33.9	32.8	67.5
L9901 coi	I (on power board)	40.9	39.1	87.5
PCB near	BD9902 (on power board)	34.1	33.6	87.5
U902 Bod	ly	39.7	38.5	82.5
C901 (on	power board)	33.1	32.8	87.5
T901 coil	(on power board)	53.4	50.7	92.5
T901 core	e (on power board)	50.9	49.5	92.5
PCB near	Q901 (on power board)	41.9	40.1	87.5
		i	-i	i

40.7

39.9

31.3

29.1

26.7

33.3

40.3

38.3

30.1

27.9

25.3

31.9

87.5

87.5

57.5

77.5

77.5

TRF No. IEC60950_1F

Plastic enclosure outside

Metal enclosure

Panel surface

PCB near Main IC (main board)

PCB near L801 (on power board)

Plastic enclosure inside near T901

Page 38 of 45

Report No. 17051179 002

IEC 60950-1

Clause	Dequirement Test								
	Requirement + Test					Result -	Remark		Verdict
Ambient					22.7		2	2.5	
At vertical o	prientation		<u> </u>						
Line pin of <i>i</i>	AC Inlet CN901 (on powe	er board)			30.8		2	9.3	51.3
Switch body	y(on power board)				29.7		2	8.9	61.3
C9901 body	y (on power board)				31.3		3	0.7	66.3
C9903 (on	power board)				31.3		3	0.3	66.3
C9904 body	y (on power board)				32.7		3	1.9	66.3
L9901 coil (on power board)				40.3		3	8.8	86.3
PCB near E	BD9902 (on power board)		33.5		32.8		86.3	
U902 Body				39.6		38.3		81.3	
C901 (on p	ower board)			32.6			31.9		86.3
T901 coil (c	on power board)			52.1			5	0.5	91.3
T901 core (on power board)			50.1			49.3		91.3
PCB near C	Q901 (on power board)			41.3			39.8		86.3
PCB near N	/lain IC (main board)			39.8		39.5		86.3	
PCB near L	.801 (on power board)			39.4		37.6		86.3	
Metal enclo	sure			30.7			29.5		56.3
Plastic encl	osure inside near T901			28.9			27.3		
Plastic encl	osure outside				26.3		24.8		76.3
Panel surfa	се				31.9		3	0.1	76.3
Ambient				21.5			21.3		
Suppleme	ntary information:								
	re T of winding:	t ₁ (°C)	R ₁	(Ω)	t ₂ (°C)	R ₂ (Ω)	T (°C)	Allowed T _{max} (°C)	Insulation class

Supplementary information:

1. The temperatures were measured under the worst case normal mode defined in 1.2.2.1 and as described in sub-clause 1.6.2 at voltages as described above.

2. With a specified ambient temperature of 40°C, and the minimum ambient temperature during test Tam, Temperature is calculated as follows:

Winding components providing safety isolation:

- T901, Class B \rightarrow T_{max} = 120°C - 10°C - 40°C+ Tamb.

Components with maximum absolute temperature of others:

Tmax= Tmax of component – 40+Tamb.

_

Page 39 of 45

Report No. 17051179 002

IEC 60950-1

Clause Requirement + Test Result - Remark Verd
--

4.5.5	TABLE: ball pressure test of thermoplastic parts				
	allowed impression diameter (mm): $\leq 2 \text{ mm}$				
Part		Test temperature (°C)		on diameter mm)	
Note(s):					

4.6.1, 4.6.2 Table: enclosu	re openings		Р
Location	Size (mm)	Comments	
Internal metal enclosure type	B, a) at horizontal orientation; b) a	t vertical orientation	
a) Top b) Right	1) Numerous circle openings: Ø4.8mm;	: 1) Openings do not exceed 5mm in an dimension. No hazards.	
	2) One rectangle openings	2) Covered by plastic enclosure,	no hazards.
	above main board: 40.0mm x 6.9mm;	3) No hazardous part within vertical projection of 5° from the opening.	
	 2) One oval opening above main board for speaker wires: 19.6m x 10.1mm. 		
a) Rear b) Rear	Numerous circle openings above main board: Ø6.5mm x 3; Ø5.5mm x 4	No hazardous part within vertical 5° from the opening.	projection of
a) Left b) Top	Numerous circle openings: Ø4.8mm	Openings do not exceed 5mm in dimension. No hazards.	any
a) Right b) Bottom	No opening.		
a) Bottom b) Left	 Under power board side: Numerous Ø1.86mm holes; spacing of holes (centre to centre): 3.2 mm; thickness of metal: min.0.81mm. 	 Comply with table 4D. Main board is supplied by LPS for fire enclosure. 	, not required
	 Under main board side: two Ø3.0mm holes. 		

4.7	TABLE:	Resistance to fire					Р
Par	t	Manufacturer of material	Type of material	Thickness (mm)	Flammability class	E	vidence
PCB					V-1		UL

Page 40 of 45

Report No. 17051179 002

IEC 60950-1

Clause	Requirement + Test	Result - Remark	Verdict

Supplementary information: See table 1.5.1.

* Not fire enclosure.

5.1	TABLE: touch curre	urrent measurement			Р	
Measured between:		Measured (mA)	Limit (mA)	Comments/conditions		
L – metal er	nclosure	0.47	3.5	Switch "e" open		
N – metal enclosure		0.45	3.5	Switch "e" open		
L – signal co	onnector	0.08	0.25	Switch "e" close *		
N – signal c	onnector	0.08	0.25	Switch "e" close *		
L – plastic e	nclosure	0.005	0.25	Switch "e" close		
N – plastic enclosure 0.005 0.25		0.25	Switch "e" close			
Supplementary information: Supplied with 264V/60Hz.						
* Test series a with functional contains discomposed						

* Test performed with functional earthing disconnected.

5.2	TABLE: Electric strength tests, impulse tes	ts and voltage surg	e tests	Р
Test voltage	e applied between:	Voltage shape (AC, DC, impulse, surge)	Test voltage (V)	Breakdown Yes / No
Test with 23	3.6 inch models			
Basic/suppl	lementary:			
Unit primary	y to earthed metal part	AC	1740	No
Mylar sheet	between power board and metal enclosure	AC	1740	No
Reinforced:	:	·	·	
L/N to acce	essible plastic enclosure with metal foil	AC	3000	No
Unit primary	y to secondary (output)	AC	3000	No
T901 ¹⁾ : prin	nary to secondary	AC	3000	No
T901 ¹⁾ : sec	condary to core	AC	3000	No
T901 ¹⁾ : eac	ch layer of insulation tape	AC	3000	No
Supplemen	ntary information:	· ·		
1. For all	sources of T901;			
2) Test aft	ter humidity conditioning test.			

Page 41 of 45

Report No. 17051179 002

IEC 60950-1

Result - Remark

Verdict

5.3	ТА	BLE: Fault co	ndition tes	sts				Р
	Ambient temperature (°C) See below							
	Power source for EUT: Manufacturer, model/type, output rating							
Component No.		Fault	Supply voltage (V)	Test time	Fuse #	Fuse current (A)	rent	
Test with po	owe	r board 715G7	775 on 23.	6 inch mo	dels			
T901 Pin 1 t pin 2	:0	S-C	240	5 min	F9901	0.06	Unit shutdown, no hazards.	
T901 Pin 4 t pin 5	:0	S-C	240	5 min	F9901	0.06	Unit shutdown, no hazards.	
T901 pin 6,7 to pin 8,9		S-C	240	10 min	F9901	0.03	Unit shutdown, no hazards.	
T901 pin 8,9 to pin 10		S-C	240	5 min	F9901	0.06	Unit shutdown, no hazards.	
BD9902 pin 1- 3		S-C	240	<1 sec	F9901		F9901 opened instantly, no hazards.	
D801		S-C	240	<1 sec	F9901	0.02	Unit shutdown, no hazards.	
U901 pin 5-4	4	S-C	240	5 min	F9901	0.02	Unit shutdown, no hazards.	
U901 pin 5-1		S-C	240	5 min	F9901	0.05	Unit shutdown, no hazards.	
U901 pin 6-1	1	S-C	240	5 min	F9901	0.05	Unit shutdown, no hazards.	
U902 Pin 1-2	2	S-C	240	10 min	F9901	0.05	Unit shutdown, no hazards.	
U902 Pin 3-4	4	S-C	240	10 min	F9901	0.05	Unit shutdown, no hazards.	
U902 Pin 1		O-C	240	10 min	F9901	0.05	Unit shutdown, no hazards.	
Q9101 pin G S	<u>-</u>	S-C	240	5 min	F9901	0.04	Unit shut down, no hazard	
Q1901 pin D- G ⁴⁾		S-C	240	5 min	F9901	0.04	Q901, R909 damaged. No hazards.	
Q9101 pin D- S		S-C	240	5 min	F9901	0.04	Q901, R914 damaged. No hazards.	
+16V to eart	th	S-C	240	5 min	F9901	0.04	Unit shutdown, no hazards.	
+5V to earth	1	S-C	240	5 min	F9901	0.04	Unit shutdown, no hazards.	
D910		S-C	240	5 min	F9901	0.04	Unit shutdown, no hazar	ds.
Overload +16V after F801		o-l	240	8.5hrs	F9901	0.42	Max. Measured temp.in T901 coil=91.1°C, T901 core=86.7°C, U902= 67.8°C, ambient= 20.8°C, before down winding is loaded t No damage, no hazards.	o 3.0A.

Clause

Requirement + Test

Page 42 of 45

Report No. 17051179 002

IEC 60950-1

Requirement + Test **Result - Remark** Verdict Clause Overload +5V o-l 240 8.5hrs F9901 0.41 Max. Measured temp.in after F901 T901 coil=88.6°C, T901 core=83.7°C, U902= 65.5°C, ambient= 20.7°C, before shut down winding is loaded to 7.1A. No damage, no hazards. 0.28 Ventilation blocked 240 4.9hrs F9901 Max. Measured temp.in openings for T901 coil=55.1°C. 23.6 inch T901 core=52.9°C, models U902= 40.5°C, ambient=21.3°C. No damage, no hazards. blocked 240 F9901 0.28 Ventilation 4.9hrs Max. Measured temp.in T901 coil=58.3°C, openings for 27 inch T901 core=55.1°C, models U902= 41.7°C, ambient=19.3°C. No damage, no hazards. 240 2hrs F9901 0.20 Speaker s-c Max. Measured temp.in T901 coil=53.3°C, T901 core=50.8°C, U902=38.1°C, ambient=20.6°C. No damage, no hazards.

Supplementary information:

1. The unit passed 3000V hi-pot test between primary and accessible output connector after single fault test above.

2. In fault column, where s-c=short-circuited, o-c=open-circuited, o-I = overload.

3. For fuse opened conditions were tested with each source of fuse.

4. For component damaged conditions have been repeated twice (three tests total) with same result.

5. Temp. limit of transformer according to table C.1 is 175°C -10°C-(40°C –Tamb).

Page 43 of 45

Report No. 17051179 002

IEC 60950-1							
Clause	Requirement + Test	Verdict					
C.2	Safety isolation transformer		Р				
	Construction details:						
Transform	ner part name: T901						
Manufactu	urer: See appended table 1.5.1						
Туре:	See appended table 1.5.1						
	ions of all sources of T901 are identical each othe difference.	r, except for model designation	on, manufacturer and				
For T901	used on power board		_				
Recurring	peak voltage	500V					
	clearance for reinforced insulation e 2H and 2J)	6.6mm					
Effective v	voltage rms	260V					
Required (from table	creepage distance for reinforced insulation e 2L)	6.6mm					
Measured	l min. creepage distance						
Location		inside (mm)	outside (mm)				
prim-sec		Triple insulation wire provided for sec. windings.	42.5mm (between primary and secondary solder pins.)				
prim-core							
sec-core		Triple insulation wire provided for sec. windings.	11.1mm (between secondary solder pir and core.)				
Measured	I min. clearances						
Location		inside (mm)	outside (mm)				
prim-sec		Triple insulation wire provided for sec. windings.	42.5mm (between primary and secondary solder pins.)				
prim-core							
sec-core		Triple insulation wire provided for sec. windings.	11.1mm (between secondary solder pir and core.)				

Report No. 17051179 002

IEC 60950-1





Concentric windings on bobbin (horizontal type core). Three layers of insulation tape around the outer winding and the outer winding is primary. Triple insulated wire used for secondary windings. The core is considered as primary part.

 Pin numbers

 Prim.
 Pin 1-2; Pin 3-4-5

 Sec.
 Pin 8,9-6,7-10

 Bobbin
 Material

 Material
 See table 1.5.1.

 Thickness
 Min. 0.45mm

 Image: Comparison of the second s

TRF No. IEC60950_1F

Page 45 of 45

Report No. 17051179 002

IEC 60950-1

Clause	Requirement + Test	Result - Remark	Verdict	
Electric strer	nath test			
	a.c. after humidity treatment			
Result		Pass		